# MSHG-500

**PS2 TYPE FIRMWARE UPDATE** 

## 1.Connection



VIA PS2 Cable
Turn off the MSHG-500 and connect cable as below



Turn on the MSHG-500 and check the LCD screen as below.



\*Note : Please use provided our PS2 cable.

# 1.Program Connect



#### Run to MSPG file transfer as below.

MP File System ROM File NvRAM File		
File Name: Open File Send File	DATA SEND C ASCIL C	CLEAR MSG HELP
	Receive Data C ASCII @	HEX Bytes Received
Send All Files         Send Selected           No         File Name [Width × Hight]         *           [01]		
6	50%	00:00[min:sec] 100%

Click COM SETUP as below.



## 1.Program Connect

## Check the COM PORT number first on your PC, and set up to as below.

RS232C Setup			×	
-RS2	32C Setup			
	COM PORT	СОМ1 -		
	Baud Rate	115200 💌		
	Data Bit	8		
	Stop Bit			
	Parity Bit	NONE		
	Connect	Disconnect		
Not Opened Any Communications!!				
			EXIT	

When you set up the COM PORT, then click Connect button.



## 2. Firmware upload



### Check the System ROM File tap, and click to Open File.

PG(VC2033) File Tra	nsfer V1.00(Beta)		
BMP File System ROM Fi	le   NvRAM File	1/0 device UART	COM SETUP EXIT
	Open File Send File CLEAR MSG File Name: msnn2033test DAT 연기 찾는 위치(!): 같 Data BMP mspg2033test DAT 파일 이름(N): mspg2033test DAT 파일 이름(N): [DATA FILE (*,DAT)	HELP   1651 1 0 1 0 b-000008 D-000008 D-000008 D-000008 D-00108 D-00008 D-0008 D-0008 P-0008 P-0008 P-0008 P-0008 P-0008 P-0008 P-0008 P-0008 P-0008 P-0008 P-0008 P-0008 P-0008 P-008 P-008 P-008 P-008 P-008 P-008	
0%	0/0	100%	

Open the provided MSPGXXXX.DAT firmware file.

## 2. Firmware upload



😹 PG(VC2033) File	Transfer V1.00(Beta)		
BMP File System RC	M File   NvRAM File	I/O device UART	COM SETUP EXIT
	Open File     Send File     CLEAR MSG       File Name:       [mspg2033test.DAT       File Info:     Make ROM       [mspg2033test.DAT       Load Completell       DAT Size 534148 Bytes       mspg2033test.DAT       Load Completell       DAT Size 534148 Bytes	ELP	
	0% 0 / 0	100%	

- Firmware will be update and you can check the LCD screen.
- When firmware update is finished, please turn off the MSHG-500.
- Please disconnect to all of cable and turn on the MSHG-500.
- END

# Thank You !

www.Ltdmaster.com